

---

# Drsstc Building The Modern Day Tesla Coil

---

Drsstc Building The Modern Day Tesla Coil

Downloaded from [cardprinter.sendafriend.co](http://cardprinter.sendafriend.co) by Arthur & Alana

---

## UNDERSTANDING THE DRSSTC: BUILDING THE MODERN DAY TESLA COIL

---

The Tesla coil has long captured the imagination of electrical engineers, hobbyists, and science enthusiasts. First invented by Nikola Tesla in 1891, this resonant transformer circuit was originally designed to produce high-voltage, low-current, high-frequency alternating current electricity. For decades, the classic spark gap Tesla coil (SGTC) dominated the landscape. However, as technology progressed, a more efficient, reliable, and powerful variant emerged: the Dual Resonant Solid State Tesla Coil, or DRSSTC. If you are considering DRSSTC building, the modern day Tesla coil, you are stepping into a world where semiconductor technology meets resonant inductive coupling, offering unparalleled control and performance. This article provides a comprehensive guide to understanding, designing, and building a DRSSTC, covering its history, working principles, key components, and practical construction tips.

## What Exactly is a DRSSTC?

A DRSSTC, or Dual Resonant Solid State Tesla Coil, is a type of Tesla coil that uses solid-state components—primarily insulated-gate bipolar transistors (IGBTs) or metal-oxide-semiconductor field-effect transistors (MOSFETs)—instead of a traditional spark gap to switch the primary circuit. The term "dual resonant" refers to the fact that both the primary and secondary LC circuits are tuned to resonate at the same frequency. This dual resonance condition maximizes energy transfer efficiency between the two coils, resulting in longer, more consistent sparks and reduced stress on components. When you are DRSSTC building, the modern day Tesla coil, you are essentially replacing the noisy, inefficient spark gap with a precisely controlled switching system that can operate at much higher repetition rates.

## The Evolution: From SGTC to DRSSTC

Traditional spark gap Tesla coils (SGTCs) rely on a mechanical or static spark gap to discharge a capacitor bank into the primary coil. While simple and visually impressive, SGTCs have several drawbacks. They produce significant electromagnetic interference, generate substantial heat, suffer from electrode erosion, and operate at relatively low repetition rates. The spark gap also limits the efficiency of energy transfer because the gap must be re-ionized each cycle.

The advent of high-power semiconductor switches in the late 20th century opened the door for solid-state Tesla coils (SSTCs). Early SSTCs used a single resonant circuit and simple feedback oscillators.

While an improvement, they still lacked the efficiency and spark length of a well-tuned SGTC. The breakthrough came with the DRSSTC, which added a second resonant tank circuit on the primary side, allowing both coils to ring at their natural frequency. This innovation dramatically improved energy transfer and reduced switching losses. Today, DRSSTC building, the modern day Tesla coil, represents the gold standard for high-performance Tesla coil construction.

## Key Components of a DRSSTC

Building a DRSSTC requires a solid understanding of several core components. Each part plays a critical role in the system's overall performance and reliability.

- **Primary Tank Circuit:** This consists of a high-voltage capacitor bank and the primary induction coil. The capacitors are arranged in a series-parallel configuration to achieve the desired capacitance and voltage rating. Polypropylene film capacitors are preferred for their low equivalent series resistance (ESR) and high current handling.
- **Secondary Resonant Circuit:** The secondary coil is typically wound on a PVC or acrylic tube using magnet wire. The number of turns and the coil geometry determine the resonant frequency. The top load, often a toroid, adds capacitance to the secondary circuit and shapes the electric field for optimal spark discharge.
- **Switching Bridge:** The heart of the DRSSTC is the full-bridge or half-bridge inverter circuit. High-power IGBTs, such as the IXYS or CM series, are commonly used. The bridge switches the DC bus voltage across the primary tank at the resonant frequency. Proper gate drive circuitry and snubber networks are essential to protect the switches from voltage spikes and ringing.
- **Controller and Feedback System:** Unlike a spark gap, the DRSSTC requires active control to maintain resonance. A feedback signal from the secondary coil is fed into a phase-locked loop (PLL) or microcontroller-based controller. This controller adjusts the switching frequency to match the resonant peak, even as the system heats up or load conditions change. Many builders use a Field-Programmable Gate Array (FPGA) or a Digital Signal Processor (DSP) for precise timing.
- **DC Power Supply:** The bus voltage for the inverter is typically provided by a variable DC power supply. For small to medium DRSSTCs, a voltage doubler circuit powered from the mains is common. Larger coils may use a three-phase rectifier and a bank of filter capacitors to provide a stable DC rail.
- **Interrupter and Modulation:** An interrupter circuit controls the on-time and off-time of the coil, allowing for adjustable spark length and duty cycle. Modern DRSSTCs often include audio modulation inputs, enabling the coil to "sing" by varying the pulse repetition rate.

# How a DRSSTC Works: The Physics and Electronics

The operational principle of a DRSSTC is based on resonant inductive coupling and zero current switching (ZCS). When the IGBT bridge switches on, current begins to flow in the primary tank circuit. Because the primary and secondary are both tuned to the same resonant frequency, energy oscillates between the primary capacitor and the primary inductor. A portion of this oscillating magnetic field couples into the secondary coil, inducing a high voltage across the secondary and the top load.

The key to efficient operation is that the switching occurs at the zero crossing of the primary current. This is known as zero current switching. When the current is zero, the IGBTs can be turned off with minimal switching losses and stress. The controller uses feedback from the secondary to track the resonant frequency and adjust the switching timing accordingly. If the switching drifts out of phase, efficiency drops dramatically, and the IGBTs can overheat and fail.

During the "on" time, the energy in the primary tank builds up in oscillation. When the interrupter turns off the bridge, the remaining energy in the primary tank is either dissipated or recovered, depending on the design. The secondary coil continues to ring, producing a series of sparks that can last for several milliseconds. When DRSSTC building, the modern day Tesla coil, understanding this resonant energy transfer is crucial for achieving long, consistent sparks.

## Building Your Own DRSSTC: Step-by-Step Considerations

Building a DRSSTC is an advanced project that requires knowledge of electronics, high-voltage safety, and mechanical construction. Below is a structured approach to designing and building your own coil.

### STEP 1: DEFINE YOUR GOALS AND BUDGET

Begin by deciding what you want to achieve. A small tabletop DRSSTC producing 6 to 12 inch sparks can be built on a modest budget using cheap IGBTs and a simple PLL controller. A giant coil capable of 10 foot sparks requires a significant investment in components, cooling, and safety equipment. Be realistic about your skill level and budget before ordering parts.

### STEP 2: DESIGN THE SECONDARY COIL

The secondary coil determines the resonant frequency and the output voltage. A typical secondary uses 800 to 1200 turns of 26 to 30 AWG magnet wire on a 4 to 6 inch diameter tube. The length of

the winding is usually 12 to 24 inches. The resonant frequency should be in the range of 150 kHz to 500 kHz for most DRSSTCs. Calculate the inductance and self-capacitance of the secondary using standard formulas or simulation software. The top load adds additional capacitance, lowering the resonant frequency.

### STEP 3: DESIGN THE PRIMARY COIL

The primary coil is typically a flat spiral or a helical coil made from copper tubing or litz wire. The number of turns is usually small, between 5 and 15 turns. The primary inductance must be such that when combined with the primary capacitor, the tank resonates at the same frequency as the secondary. A good starting point is to use a capacitor bank of 0.1 to 0.5  $\mu\text{F}$  and adjust the number of primary turns to achieve resonance.

### STEP 4: SELECT THE SWITCHING COMPONENTS

Choose IGBTs rated for at least twice the expected bus voltage and three times the peak current. For a small coil running at 300 VDC, 600 V IGBTs are adequate. For larger coils using 600 VDC or more, 1200 V devices are necessary. The gate driver must provide sufficient peak current to charge and discharge the IGBT gate capacitance quickly. Isolated gate drive power supplies are essential for the high-side switches in a full bridge.

### STEP 5: BUILD THE CONTROLLER

The controller is the brain of the DRSSTC. A simple PLL-based controller can be built using a CD4046 phase-locked loop IC and some logic gates. More advanced controllers use a microcontroller or FPGA to implement adaptive frequency tracking and protection features. The controller must generate the gate signals for the bridge and adjust the duty cycle based on feedback from the secondary coil.

### STEP 6: ASSEMBLE AND TEST

Start with low power testing. Use a variac to slowly increase the bus voltage while monitoring the primary current and the output sparks. Check the temperature of the IGBTs and the capacitors. Tune the system by adjusting the number of primary turns or the capacitor value until maximum spark length is achieved. Always have a current-limiting resistor or fuse in the DC bus to prevent catastrophic failures.

## Safety Considerations

**High voltage is lethal.** DRSSTCs operate at voltages ranging from several hundred volts on the primary side to tens or even hundreds of thousands of volts on the secondary. Even a small coil can deliver a painful and dangerous shock. Always discharge all capacitors before touching any part of the circuit. Use insulated tools and work on a rubber mat. Keep a fire extinguisher rated for electrical fires nearby. Never operate the coil alone. Ensure that all bystanders are at a safe distance, and use

a Faraday cage or shielding to protect sensitive electronics from the intense electromagnetic fields.

## Tuning and Optimization

Tuning a DRSSTC is a blend of science and art. The goal is to achieve zero current switching across the entire operating range. This requires careful adjustment of the feedback loop and the primary tank components. One common method is to use a signal generator and an oscilloscope to measure the resonant frequency of the secondary with the top load attached. Then adjust the primary tank to match. During operation, the resonant frequency can shift due to heating and arcing. A robust controller with adaptive frequency tracking is essential for consistent performance.

Optimization also involves reducing parasitic losses. Use thick copper wire or tubing for the primary to minimize resistance. Keep all connections short and direct. Use low-ESR capacitors and snubber networks to suppress voltage spikes. Proper cooling for the IGBTs and capacitors is critical for extended operation. Many builders use forced air cooling with large heatsinks or even liquid cooling for high-power coils.

## Applications and Modern Uses

While DRSSTCs are often built for entertainment and education, they have practical applications as well. They are used in high-voltage testing, plasma physics research, wireless power transmission experiments, and even in special effects for movies and live shows. The ability to modulate the output with audio signals makes DRSSTCs popular for "singing Tesla coil" performances. When you engage in DRSSTC building, the modern day Tesla coil, you are contributing to a rich tradition of innovation that started over a century ago.

## Conclusion

Building a DRSSTC is one of the most rewarding projects for anyone passionate about high-voltage electronics and resonant circuits. It combines principles of electromagnetism, power electronics, and control theory into a single, spectacular device. By replacing the old spark gap with solid-state switching, the DRSSTC offers greater efficiency, reliability, and control. Whether you are a seasoned engineer or an ambitious hobbyist, DRSSTC building, the modern day Tesla coil, is a journey that will deepen your understanding of electrical resonance and push your technical skills to new heights. Start with a small design, respect the dangers of high voltage, and enjoy the arc of discovery.